

ECODESIGN INFORMATION

Applies to non-residential ventilation units (NRVU)

According to Regulation EU No 1253/2014 of the European Commission, implementing Directive 2009/125/CE of European Parliament

SODECA, S.L.U.

www.sodeca.com

c) Typology
d) Type of drive
e) Type of HRS

g) Nominal flowrate
h) Effective electric power input
i) SFPint

k) Nominal external pressure
l) Internal pressure drop of ventilation components
m) Internal pressure drop of non-ventilation components

327/2011
o1) Max. Internal leakage index
o2) Max. External leakage index
p) Energy performance of the filters

r) LWA radiated

b)	c)	d)	e)	f)	g)	h)	i)	j)	k)	l)	m)	n)	o1)	o2)	p)	q)	r)	ERP
				%	m ³ /s	kW	W/m ³ /s	m/s	Pa	Pa	Pa	%	%	%			dBA	
SV/FILTER-125 G4+F6	NRVU / UVU	Variable Drehzahl	Kein/e		0.047	0.111	230	4.70	300	32		0.0		0.8	G4: G; F6: F	Siehe Anleitung	41	2018
SV/FILTER-150 G4+F6	NRVU / UVU	Variable Drehzahl	Kein/e		0.074	0.156	230	3.70	372	46		0.0		0.6	G4: G; F6: F	Siehe Anleitung	52	2018
SV/FILTER-200 G4+F6	NRVU / UVU	Variable Drehzahl	Kein/e		0.110	0.093	230	3.67	130	49		0.0		0.5	G4: G; F6: F	Siehe Anleitung	56	2018
SV/FILTER-250 G4+F6	NRVU / UVU	Variable Drehzahl	Kein/e		0.122	0.189	230	2.44	345	60		0.0		0.5	G4: G; F6: F	Siehe Anleitung	60	2018
SV/FILTER-315 G4+F6	NRVU / UVU	Variable Drehzahl	Kein/e		0.282	0.122	230	3.53	70	79		0.0		0.3	G4: G; F6: F	Siehe Anleitung	62	2018
SV/FILTER-350 G4+F6	NRVU / UVU	Variable Drehzahl	Kein/e		0.400	0.202	230	4.00	126	106		45.0		0.3	G4: G; F6: F	Siehe Anleitung	65	2018
SV/FILTER-400 G4+F6	NRVU / UVU	Variable Drehzahl	Kein/e		0.449	0.398	230	3.45	257	90		46.1		0.3	G4: G; F6: F	Siehe Anleitung	67	2018
SV/FILTER-125 F6+F8	NRVU / UVU	Variable Drehzahl	Kein/e		0.052	0.114	230	5.20	280	33		0.0		0.7	F6: F; F8: A	Siehe Anleitung	41	2018
SV/FILTER-150 F6+F8	NRVU / UVU	Variable Drehzahl	Kein/e		0.082	0.161	230	4.10	345	46		0.0		0.5	F6: F; F8: A	Siehe Anleitung	52	2018
SV/FILTER-200 F6+F8	NRVU / UVU	Variable Drehzahl	Kein/e		0.122	0.095	230	4.07	117	49		0.0		0.5	F6: F; F8: A	Siehe Anleitung	56	2018
SV/FILTER-250 F6+F8	NRVU / UVU	Variable Drehzahl	Kein/e		0.134	0.192	230	2.68	312	59		0.0		0.4	F6: F; F8: A	Siehe Anleitung	60	2018
SV/FILTER-315 F6+F8	NRVU / UVU	Variable Drehzahl	Kein/e		0.305	0.124	230	3.81	58	76		0.0		0.3	F6: F; F8: A	Siehe Anleitung	62	2018
SV/FILTER-350 F6+F8	NRVU / UVU	Variable Drehzahl	Kein/e		0.436	0.204	230	4.36	106	102		45.0		0.2	F6: F; F8: A	Siehe Anleitung	65	2018
SV/FILTER-400 F6+F8	NRVU / UVU	Variable Drehzahl	Kein/e		0.489	0.405	230	3.76	227	87		46.1		0.3	F6: F; F8: A	Siehe Anleitung	67	2018
SV/FILTER-125 F7+F9	NRVU / UVU	Variable Drehzahl	Kein/e		0.049	0.113	230	4.90	291	33		0.0		0.7	F7: A; F9: A	Siehe Anleitung	41	2018
SV/FILTER-150 F7+F9	NRVU / UVU	Variable Drehzahl	Kein/e		0.078	0.158	230	3.90	359	46		0.0		0.6	F7: A; F9: A	Siehe Anleitung	52	2018
SV/FILTER-200 F7+F9	NRVU / UVU	Variable Drehzahl	Kein/e		0.115	0.094	230	3.83	124	49		0.0		0.5	F7: A; F9: A	Siehe Anleitung	56	2018
SV/FILTER-250 F7+F9	NRVU / UVU	Variable Drehzahl	Kein/e		0.127	0.190	230	2.54	329	60		0.0		0.4	F7: A; F9: A	Siehe Anleitung	60	2018
SV/FILTER-315 F7+F9	NRVU / UVU	Variable Drehzahl	Kein/e		0.293	0.123	230	3.66	64	77		0.0		0.3	F7: A; F9: A	Siehe Anleitung	62	2018
SV/FILTER-350 F7+F9	NRVU / UVU	Variable Drehzahl	Kein/e		0.417	0.203	230	4.17	116	104		45.0		0.3	F7: A; F9: A	Siehe Anleitung	65	2018
SV/FILTER-400 F7+F9	NRVU / UVU	Variable Drehzahl	Kein/e		0.468	0.402	230	3.60	242	89		46.1		0.3	F7: A; F9: A	Siehe Anleitung	67	2018