

# ECODESIGN INFORMATION

Applies to non-residential ventilation units (NRVU)

According to Regulation EU No 1253/2014 of the European Commission, implementing Directive 2009/125/CE of European Parliament

SODECA, S.L.U.

www.sodeca.com

c) Typology  
d) Type of drive  
e) Type of HRS

g) Nominal flowrate  
h) Effective electric power input  
i) SFPint

k) Nominal external pressure  
l) Internal pressure drop of ventilation components  
m) Internal pressure drop of non-ventilation components

327/2011  
o1) Max. Internal leakage index  
o2) Max. External leakage index  
p) Energy performance of the filters

r) LWA radiated

b)	c)	d)	e)	f)	g)	h)	i)	j)	k)	l)	m)	n)	o1)	o2)	p)	q)	r)	ERP
				%	m <sup>3</sup> /s	kW	W/m <sup>3</sup> /s	m/s	Pa	Pa	Pa	%	%	%			dBA	
RFV-280-4T-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		0.349	0.076		3.89	57			0.0			Entfällt	Entfällt		2018
RFV-280-4M-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		0.349	0.076		3.89	57			0.0			Entfällt	Entfällt		2018
RFV-315-4T-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		0.497	0.142		4.48	85			41.2			Entfällt	Entfällt		2018
RFV-315-4M-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		0.497	0.142		4.48	85			42.0			Entfällt	Entfällt		2018
RFV-315-6T-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		0.362	0.034		3.27	19			0.0			Entfällt	Entfällt		2018
RFV-315-6M-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		0.362	0.034		3.27	19			0.0			Entfällt	Entfällt		2018
RFV-355-4T-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		0.757	0.251		5.43	111			45.0			Entfällt	Entfällt		2018
RFV-355-4M-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		0.757	0.251		5.43	111			43.5			Entfällt	Entfällt		2018
RFV-355-6T-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		0.505	0.068		3.62	34			0.0			Entfällt	Entfällt		2018
RFV-355-6M-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		0.505	0.068		3.62	34			40.6			Entfällt	Entfällt		2018
RFV-400-4T-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		1.260	0.364		6.27	103			50.4			Entfällt	Entfällt		2018
RFV-400-4M-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		1.229	0.425		6.11	127			48.1			Entfällt	Entfällt		2018
RFV-400-6T-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		0.793	0.162		3.94	63			43.4			Entfällt	Entfällt		2018
RFV-400-6M-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		0.793	0.162		3.94	63			45.5			Entfällt	Entfällt		2018
RFV-450-4T-F-400 IE3	NRVU / UVU	Variable Drehzahl	Kein/e		1.773	0.463		8.36	97			60.8			Entfällt	Entfällt		2018
RFV-450-4M-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		1.689	0.628		7.96	145			48.3			Entfällt	Entfällt		2018
RFV-450-6T-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		1.121	0.230		5.29	67			48.9			Entfällt	Entfällt		2018
RFV-450-6M-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		1.121	0.230		5.29	67			51.3			Entfällt	Entfällt		2018
RFV-500-4T-F-400 IE3	NRVU / UVU	Variable Drehzahl	Kein/e		2.722	0.585		9.63	83			60.6			Entfällt	Entfällt		2018
RFV-500-6T-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		1.733	0.266		6.13	52			54.1			Entfällt	Entfällt		2018
RFV-500-6M-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		1.733	0.266		6.13	52			47.6			Entfällt	Entfällt		2018
RFV-630-6T-F-400 IE3	NRVU / UVU	Variable Drehzahl	Kein/e		2.927	0.954		6.60	136			62.9			Entfällt	Entfällt		2018
RFV-710-6T-F-400 IE3	NRVU / UVU	Variable Drehzahl	Kein/e		2.360	2.461		4.23	496			59.4			Entfällt	Entfällt		2018
RFV-800-6T-F-400 IE3	NRVU / UVU	Variable Drehzahl	Kein/e		5.028	3.965		7.14	398			63.0			Entfällt	Entfällt		2018
RFV-800-8T-F-400	NRVU / UVU	Variable Drehzahl	Kein/e		4.178	1.723		5.94	187			58.0			Entfällt	Entfällt		2018