

ECODESIGN INFORMATION

Applies to non-residential ventilation units (NRVU)

According to Regulation EU No 1253/2014 of the European Commission, implementing Directive 2009/125/CE of European Parliament

SODECA, S.L.U.

www.sodeca.com

- b) Model
- c) Typology
- d) Drive type
- e) HRS type
- f) Thermal efficiency of heat recovery (%)
- g) Nominal flowrate
- h) Effective electric power input
- i) SFPint
- j) Face velocity at design flow rate
- k) Nominal external pressure
- l) Internal pressure drop of ventilation components
- m) Internal pressure drop of non-ventilation components
- n) Static efficiency of fans according to (EU) 327/2011
- o1) Max. internal leakage rate
- o2) Max. external leakage rate
- p) Energy performance of the filters
- q) Visual filter warning
- r) LWA radiated

b)	c)	d)	e)	f)	g)	h)	i)	j)	k)	l)	m)	n)	o1)	o2)	p)	q)	r)	ERP
				%	m³/s	kW	W/m³/s	m/s	Pa	Pa	Pa	%	%	%			dBA	
UFX-12/12-0.5 G4+F6	NRVU / UVU	Variabel hastighet	Ingen	0.704	0.426	230	2.09	138	84			35.7	2.4		G4: G; F6: F	Se manual	70	2018
UFX-12/12-0.75 G4+F6	NRVU / UVU	Variabel hastighet	Ingen	0.723	0.537	230	2.15	198	89			38.9	2.4		G4: G; F6: F	Se manual	73	2018
UFX-12/12-1 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	0.742	0.653	230	2.20	264	94			40.2	2.4		G4: G; F6: F	Se manual	76	2018
UFX-12/12-1.5 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	0.738	0.801	230	2.19	345	93			41.4	2.4		G4: G; F6: F	Se manual	78	2018
UFX-12/12-2 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	0.713	1.165	230	2.12	527	86			42.2	2.4		G4: G; F6: F	Se manual	81	2018
UFX-12/12-3 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	0.703	1.369	230	2.09	627	84			42.5	2.4		G4: G; F6: F	Se manual	85	2018
UFX-15/15-0.75 G4+F6	NRVU / UVU	Variabel hastighet	Ingen	1.456	0.697	230	2.22	84	77			37.8	2.4		G4: G; F6: F	Se manual	74	2018
UFX-15/15-1 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.560	0.935	230	2.38	143	89			39.9	2.4		G4: G; F6: F	Se manual	77	2018
UFX-15/15-1.5 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.594	1.071	230	2.43	178	93			41.0	2.4		G4: G; F6: F	Se manual	78	2018
UFX-15/15-2 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.626	1.377	230	2.48	259	97			41.9	2.4		G4: G; F6: F	Se manual	79	2018
UFX-15/15-3 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.640	1.716	230	2.50	348	98			42.2	2.4		G4: G; F6: F	Se manual	81	2018
UFX-15/15-4 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.639	2.097	230	2.50	447	98			42.3	2.4		G4: G; F6: F	Se manual	83	2018
UFX-18/18-1.5 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.399	0.975	230	2.13	174	85			49.0	2.4		G4: G; F6: F	Se manual	78	2018
UFX-18/18-2 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.393	1.278	230	2.12	253	85			50.0	2.4		G4: G; F6: F	Se manual	83	2018
UFX-18/18-3 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.386	1.574	230	2.11	330	84			50.3	2.4		G4: G; F6: F	Se manual	83	2018
UFX-18/18-4 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.362	2.068	230	2.08	453	81			50.4	2.4		G4: G; F6: F	Se manual	85	2018
UFX-18/18-5.5 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.333	2.639	230	2.03	590	78			51.4	2.4		G4: G; F6: F	Se manual	86	2018
UFX-20/20-2 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	2.812	1.577	230	2.29	92	64			41.9	2.4		G4: G; F6: F	Se manual	75	2018
UFX-20/20-3 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	2.918	2.024	230	2.37	138	69			42.2	2.4		G4: G; F6: F	Se manual	79	2018
UFX-20/20-4 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.038	3.096	230	2.47	255	74			42.3	2.4		G4: G; F6: F	Se manual	81	2018
UFX-20/20-5.5 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.076	3.687	230	2.50	321	76			43.0	2.4		G4: G; F6: F	Se manual	83	2018
UFX-20/20-7.5 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.100	5.024	230	2.52	468	77			43.9	2.4		G4: G; F6: F	Se manual	85	2018
UFX-20/20-10 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.087	6.229	230	2.51	597	77			44.3	2.4		G4: G; F6: F	Se manual	86	2018
UFX-22/22-2 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	2.962	1.488	230	2.41	105	88			43.9	2.4		G4: G; F6: F	Se manual	75	2018
UFX-22/22-3 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.037	1.893	230	2.47	159	93			44.1	2.4		G4: G; F6: F	Se manual	79	2018
UFX-22/22-4 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.085	2.346	230	2.51	221	96			44.2	2.4		G4: G; F6: F	Se manual	81	2018
UFX-22/22-5.5 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.121	3.402	230	2.54	367	98			45.0	2.4		G4: G; F6: F	Se manual	83	2018
UFX-22/22-7.5 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.138	3.981	230	2.55	448	99			46.0	2.4		G4: G; F6: F	Se manual	84	2018
UFX-22/22-10 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.138	5.300	230	2.55	630	99			46.3	2.4		G4: G; F6: F	Se manual	88	2018
UFX-22/22-15 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.146	6.004	230	2.56	728	100			46.4	2.4		G4: G; F6: F	Se manual	89	2018
UFX-25/25-3 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	4.358	2.080	230	2.21	84	78			42.1	2.4		G4: G; F6: F	Se manual	79	2018
UFX-25/25-4 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	4.556	2.745	230	2.31	138	85			42.2	2.4		G4: G; F6: F	Se manual	81	2018
UFX-25/25-5.5 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	4.702	3.516	230	2.39	204	91			42.9	2.4		G4: G; F6: F	Se manual	83	2018
UFX-25/25-7.5 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	4.834	4.889	230	2.45	325	96			43.8	2.4		G4: G; F6: F	Se manual	85	2018
UFX-25/25-10 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	4.883	5.944	230	2.48	419	98			44.1	2.4		G4: G; F6: F	Se manual	87	2018
UFX-25/25-15 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	4.903	7.761	230	2.49	579	98			44.3	2.4		G4: G; F6: F	Se manual	90	2018
UFX-30/28-3 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	6.935	2.561	230	2.38	47	78			43.7	2.4		G4: G; F6: F	Se manual	81	2018
UFX-30/28-4 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	7.243	3.133	230	2.48	75	85			43.8	2.4		G4: G; F6: F	Se manual	83	2018
UFX-30/28-5.5 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	7.720	4.468	230	2.65	146	96			44.6	2.4		G4: G; F6: F	Se manual	84	2018
UFX-30/28-7.5 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	8.078	5.993	230	2.77	235	105			45.6	2.4		G4: G; F6: F	Se manual	84	2018
UFX-30/28-10 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	8.231	6.807	230	2.82	284	109			45.9	2.4		G4: G; F6: F	Se manual	85	2018
UFX-30/28-15 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	8.537	9.570	230	2.93	456	118			46.0	2.4		G4: G; F6: F	Se manual	87	2018
UFX-30/28-20 G4+F6 IE3	NRVU / UVU	Variabel hastighet	Ingen	8.625	10.552	230	2.96	519	120			45.9	2.4		G4: G; F6: F	Se manual	89	2018
UFX-12/12-0.5 F6+F8	NRVU / UVU	Variabel hastighet	Ingen	0.788	0.464	230	2.34	130	83			35.7	2.4		F6: F; F8: A	Se manual	70	2018
UFX-12/12-0.75 F6+F8	NRVU / UVU	Variabel hastighet	Ingen	0.815	0.585	230	2.42	189	89			38.9	2.4		F6: F; F8: A	Se manual	73	2018
UFX-12/12-1 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	0.843	0.712	230	2.50	255	95			40.2	2.4		F6: F; F8: A	Se manual	76	2018
UFX-12/12-1.5 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	0.846	0.873	230	2.51	335	96			41.4	2.4		F6: F; F8: A	Se manual	78	2018
UFX-12/12-2 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	0.828	1.265	230	2.46	520	92			42.2	2.4		F6: F; F8: A	Se manual	81	2018
UFX-12/12-3 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	0.821	1.484	230	2.44	621	91			42.5	2.4		F6: F; F8: A	Se manual	85	2018
UFX-15/15-0.75 F6+F8	NRVU / UVU	Variabel hastighet	Ingen	1.583	0.776	230	2.41	77	68			37.8	2.4		F6: F; F8: A	Se manual	74	2018
UFX-15/15-1 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.726	1.055	230	2.63	135	81			39.9	2.4		F6: F; F8: A	Se manual	77	2018
UFX-15/15-1.5 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.779	1.214	230	2.71	170	86			41.0	2.4		F6: F; F8: A	Se manual	78	2018
UFX-15/15-2 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.847	1.574	230	2.82	252	93			41.9	2.4		F6: F; F8: A	Se manual	79	2018
UFX-15/15-3 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.890	1.967	230	2.88	344	98			42.2	2.4		F6: F; F8: A	Se manual	81	2018
UFX-15/15-4 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.909	2.403	230	2.91	445	100			42.3	2.4		F6: F; F8: A	Se manual	83	2018
UFX-18/18-1.5 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.580	1.067	230	2.41	166	86			49.0	2.4		F6: F; F8: A	Se manual	78	2018

ECODESIGN INFORMATION

Applies to non-residential ventilation units (NRVU)

According to Regulation EU No 1253/2014 of the European Commission, implementing Directive 2009/125/CE of European Parliament

SODECA, S.L.U.

www.sodeca.com

b)	c)	d)	e)	f)	g)	h)	i)	j)	k)	l)	m)	n)	o1)	o2)	p)	q)	r)	ERP
				%	m³/s	kW	W/m³/s	m/s	Pa	Pa	Pa	%	%	%			dBA	
UFX-18/18-2 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.586	1.400	230	2.42	246	87			50.0	2.4		F6: F; F8: A	Se manual	83	2018
UFX-18/18-3 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.587	1.725	230	2.42	323	87			50.3	2.4		F6: F; F8: A	Se manual	83	2018
UFX-18/18-4 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.569	2.263	230	2.39	447	85			50.4	2.4		F6: F; F8: A	Se manual	85	2018
UFX-18/18-5.5 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.545	2.884	230	2.36	585	82			51.4	2.4		F6: F; F8: A	Se manual	86	2018
UFX-20/20-2 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.070	1.596	230	2.50	69	55			41.9	2.4		F6: F; F8: A	Se manual	75	2018
UFX-20/20-3 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.231	2.085	230	2.63	110	61			42.2	2.4		F6: F; F8: A	Se manual	79	2018
UFX-20/20-4 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.449	3.303	230	2.80	220	69			42.3	2.4		F6: F; F8: A	Se manual	81	2018
UFX-20/20-5.5 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.529	3.989	230	2.87	285	73			43.0	2.4		F6: F; F8: A	Se manual	83	2018
UFX-20/20-7.5 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.624	5.546	230	2.95	433	77			43.9	2.4		F6: F; F8: A	Se manual	85	2018
UFX-20/20-10 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.662	6.937	230	2.98	566	78			44.3	2.4		F6: F; F8: A	Se manual	86	2018
UFX-22/22-2 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.246	1.590	230	2.64	93	83			43.9	2.4		F6: F; F8: A	Se manual	75	2018
UFX-22/22-3 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.362	2.040	230	2.73	145	89			44.1	2.4		F6: F; F8: A	Se manual	79	2018
UFX-22/22-4 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.442	2.546	230	2.80	206	93			44.2	2.4		F6: F; F8: A	Se manual	81	2018
UFX-22/22-5.5 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.522	3.734	230	2.86	352	97			45.0	2.4		F6: F; F8: A	Se manual	83	2018
UFX-22/22-7.5 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.553	4.385	230	2.89	433	99			46.0	2.4		F6: F; F8: A	Se manual	84	2018
UFX-22/22-10 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.570	5.870	230	2.90	615	100			46.3	2.4		F6: F; F8: A	Se manual	88	2018
UFX-22/22-15 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.585	6.660	230	2.92	714	101			46.4	2.4		F6: F; F8: A	Se manual	89	2018
UFX-25/25-3 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	4.722	2.251	230	2.40	74	69			42.1	2.4		F6: F; F8: A	Se manual	79	2018
UFX-25/25-4 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	4.991	2.977	230	2.53	122	77			42.2	2.4		F6: F; F8: A	Se manual	81	2018
UFX-25/25-5.5 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	5.207	3.818	230	2.64	183	84			42.9	2.4		F6: F; F8: A	Se manual	83	2018
UFX-25/25-7.5 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	5.439	5.311	230	2.76	296	91			43.8	2.4		F6: F; F8: A	Se manual	85	2018
UFX-25/25-10 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	5.548	6.455	230	2.81	385	95			44.1	2.4		F6: F; F8: A	Se manual	87	2018
UFX-25/25-15 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	5.647	8.424	230	2.87	540	98			44.3	2.4		F6: F; F8: A	Se manual	90	2018
UFX-30/28-3 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	7.401	2.670	230	2.54	37	64			43.7	2.4		F6: F; F8: A	Se manual	81	2018
UFX-30/28-4 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	7.795	3.299	230	2.67	60	71			43.8	2.4		F6: F; F8: A	Se manual	83	2018
UFX-30/28-5.5 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	8.446	4.803	230	2.89	124	84			44.6	2.4		F6: F; F8: A	Se manual	84	2018
UFX-30/28-7.5 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	8.962	6.563	230	3.07	206	94			45.6	2.4		F6: F; F8: A	Se manual	84	2018
UFX-30/28-10 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	9.186	7.512	230	3.15	254	99			45.9	2.4		F6: F; F8: A	Se manual	85	2018
UFX-30/28-15 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	9.675	10.764	230	3.31	423	110			46.0	2.4		F6: F; F8: A	Se manual	87	2018
UFX-30/28-20 F6+F8 IE3	NRVU / UVU	Variabel hastighet	Ingen	9.815	11.920	230	3.36	485	113			45.9	2.4		F6: F; F8: A	Se manual	89	2018
UFX-12/12-0.5 F7+F9	NRVU / UVU	Variabel hastighet	Ingen	0.744	0.444	230	2.21	134	84			35.7	2.4		F7: A; F9: A	Se manual	70	2018
UFX-12/12-0.75 F7+F9	NRVU / UVU	Variabel hastighet	Ingen	0.767	0.559	230	2.28	194	89			38.9	2.4		F7: A; F9: A	Se manual	73	2018
UFX-12/12-1 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	0.789	0.680	230	2.34	260	95			40.2	2.4		F7: A; F9: A	Se manual	76	2018
UFX-12/12-1.5 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	0.789	0.835	230	2.34	340	94			41.4	2.4		F7: A; F9: A	Se manual	78	2018
UFX-12/12-2 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	0.767	1.211	230	2.28	524	89			42.2	2.4		F7: A; F9: A	Se manual	81	2018
UFX-12/12-3 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	0.758	1.422	230	2.25	624	87			42.5	2.4		F7: A; F9: A	Se manual	85	2018
UFX-15/15-0.75 F7+F9	NRVU / UVU	Variabel hastighet	Ingen	1.518	0.735	230	2.31	81	73			37.8	2.4		F7: A; F9: A	Se manual	74	2018
UFX-15/15-1 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.640	0.991	230	2.50	139	86			39.9	2.4		F7: A; F9: A	Se manual	77	2018
UFX-15/15-1.5 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.683	1.137	230	2.57	175	90			41.0	2.4		F7: A; F9: A	Se manual	78	2018
UFX-15/15-2 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.731	1.468	230	2.64	256	95			41.9	2.4		F7: A; F9: A	Se manual	79	2018
UFX-15/15-3 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.757	1.830	230	2.68	347	98			42.2	2.4		F7: A; F9: A	Se manual	81	2018
UFX-15/15-4 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.764	2.234	230	2.69	447	99			42.3	2.4		F7: A; F9: A	Se manual	83	2018
UFX-18/18-1.5 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.484	1.018	230	2.26	170	86			49.0	2.4		F7: A; F9: A	Se manual	78	2018
UFX-18/18-2 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.484	1.335	230	2.26	250	86			50.0	2.4		F7: A; F9: A	Se manual	83	2018
UFX-18/18-3 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.480	1.644	230	2.26	327	85			50.3	2.4		F7: A; F9: A	Se manual	83	2018
UFX-18/18-4 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.458	2.158	230	2.22	451	83			50.4	2.4		F7: A; F9: A	Se manual	85	2018
UFX-18/18-5.5 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	1.431	2.752	230	2.18	588	80			51.4	2.4		F7: A; F9: A	Se manual	86	2018
UFX-20/20-2 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	2.938	1.592	230	2.39	81	60			41.9	2.4		F7: A; F9: A	Se manual	75	2018
UFX-20/20-3 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.070	2.061	230	2.50	125	65			42.2	2.4		F7: A; F9: A	Se manual	79	2018
UFX-20/20-4 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.233	3.204	230	2.63	240	72			42.3	2.4		F7: A; F9: A	Se manual	81	2018
UFX-20/20-5.5 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.289	3.839	230	2.67	306	75			43.0	2.4		F7: A; F9: A	Se manual	83	2018
UFX-20/20-7.5 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.344	5.274	230	2.72	454	78			43.9	2.4		F7: A; F9: A	Se manual	85	2018
UFX-20/20-10 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.354	6.558	230	2.73	585	78			44.3	2.4		F7: A; F9: A	Se manual	86	2018
UFX-22/22-2 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.099	1.538	230	2.52	99	86			43.9	2.4		F7: A; F9: A	Se manual	75	2018
UFX-22/22-3 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.192	1.964	230	2.60	153	91			44.1	2.4		F7: A; F9: A	Se manual	79	2018
UFX-22/22-4 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.254	2.442	230	2.65	214	95			44.2	2.4		F7: A; F9: A	Se manual	81	2018
UFX-22/22-5.5 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.309	3.559	230	2.69	360	98			45.0	2.4		F7: A; F9: A	Se manual	83	2018
UFX-22/22-7.5 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.331	4.171	230	2.71	441	99			46.0	2.4		F7: A; F9: A	Se manual	84	2018
UFX-22/22-10 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.338	5.567	230	2.71	623	100			46.3	2.4		F7: A; F9: A	Se manual	88	2018
UFX-22/22-15 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	3.349	6.310	230	2.72	722	100			46.4	2.4		F7: A; F9: A	Se manual	89	2018
UFX-25/25-3 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	4.533	2.160	230	2.30	79	74			42.1	2.4		F7: A; F9: A	Se manual	79	2018
UFX-25/25-4 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	4.765	2.853	230	2.42	130	81			42.2	2.4		F7: A; F9: A	Se manual	81	2018
UFX-25/25-5.5 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	4.943	3.655	230	2.51	194	88			42.9	2.4		F7: A; F9: A	Se manual	83	2018
UFX-25/25-7.5 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen	5.121	5.083	230	2.60	312	94			43.8	2.4		F7: A; F9: A	Se manual	85	2018

ECODESIGN INFORMATION

Applies to non-residential ventilation units (NRVU)

According to Regulation EU No 1253/2014 of the European Commission, implementing Directive 2009/125/CE of European Parliament

SODECA, S.L.U.

www.sodeca.com

b)	c)	d)	e)	f)	g)	h)	i)	j)	k)	l)	m)	n)	o1)	o2)	p)	q)	r)	ERP
				%	m ³ /s	kW	W/m ³ /s	m/s	Pa	Pa	Pa	%	%	%			dB(A)	
UFX-25/25-10 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen		5.197	6.179	230	2.64	404	97		44.1	2.4		F7: A; F9: A	Se manual	87	2018
UFX-25/25-15 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen		5.252	8.065	230	2.66	561	99		44.3	2.4		F7: A; F9: A	Se manual	90	2018
UFX-30/28-3 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen		7.165	2.618	230	2.45	42	72		43.7	2.4		F7: A; F9: A	Se manual	81	2018
UFX-30/28-4 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen		7.513	3.219	230	2.57	68	79		43.8	2.4		F7: A; F9: A	Se manual	83	2018
UFX-30/28-5.5 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen		8.070	4.636	230	2.76	136	91		44.6	2.4		F7: A; F9: A	Se manual	84	2018
UFX-30/28-7.5 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen		8.498	6.271	230	2.91	222	101		45.6	2.4		F7: A; F9: A	Se manual	84	2018
UFX-30/28-10 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen		8.682	7.148	230	2.97	271	105		45.9	2.4		F7: A; F9: A	Se manual	85	2018
UFX-30/28-15 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen		9.068	10.131	230	3.11	442	115		46.0	2.4		F7: A; F9: A	Se manual	87	2018
UFX-30/28-20 F7+F9 IE3	NRVU / UVU	Variabel hastighet	Ingen		9.179	11.190	230	3.14	505	117		45.9	2.4		F7: A; F9: A	Se manual	89	2018