

ECODESIGN INFORMATION

Applies to non-residential ventilation units (NRVU)

According to Regulation EU No 1253/2014 of the European Commission, implementing Directive 2009/125/CE of European Parliament

SODECA, S.L.U.

www.sodeca.com

- b) Model
- c) Typology
- d) Drive type
- e) HRS type
- f) Thermal efficiency of heat recovery (%)
- g) Nominal flowrate
- h) Effective electric power input
- i) SFPint
- j) Face velocity at design flow rate
- k) Nominal external pressure
- l) Internal pressure drop of ventilation components
- m) Internal pressure drop of non-ventilation components
- n) Static efficiency of fans according to (EU) 327/2011
- o1) Max. internal leakage rate
- o2) Max. external leakage rate
- p) Energy performance of the filters
- q) Visual filter warning
- r) LWA radiated

| b) | c) | d) | e) | f) | g) | h) | i) | j) | k) | l) | m) | n) | o1) | o2) | p) | q) | r) | ERP |
|----------------------|------------|--------------------|-------|----|-------|-------|--------|------|-----|----|----|------|-----|-----|--------------|--------------|-----|------|
| | | | | % | m³/s | kW | W/m³/s | m/s | Pa | Pa | Pa | % | % | % | | | dBA | |
| RFV-280-4T-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 0.349 | 0.076 | 218 | 3.89 | 57 | | | 38.9 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-280-4M-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 0.349 | 0.076 | 218 | 3.89 | 57 | | | 38.9 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-315-4T-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 0.497 | 0.142 | 230 | 4.48 | 85 | | | 41.2 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-315-4M-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 0.497 | 0.142 | 230 | 4.48 | 85 | | | 42.0 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-315-6T-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 0.362 | 0.034 | 94 | 3.27 | 19 | | | 44.0 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-315-6M-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 0.362 | 0.034 | 94 | 3.27 | 19 | | | 44.0 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-355-4T-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 0.757 | 0.251 | 230 | 5.43 | 111 | | | 45.0 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-355-4M-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 0.757 | 0.251 | 230 | 5.43 | 111 | | | 43.5 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-355-6T-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 0.505 | 0.068 | 135 | 3.62 | 34 | | | 43.5 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-355-6M-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 0.505 | 0.068 | 135 | 3.62 | 34 | | | 40.6 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-400-4T-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 1.260 | 0.364 | 230 | 6.27 | 103 | | | 50.4 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-400-4M-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 1.229 | 0.425 | 230 | 6.11 | 127 | | | 48.1 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-400-6T-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 0.793 | 0.162 | 204 | 3.94 | 63 | | | 43.4 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-400-6M-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 0.793 | 0.162 | 204 | 3.94 | 63 | | | 45.5 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-450-4T-F-400 IE3 | NRVU / UVU | Variabel hastighet | Ingen | | 1.773 | 0.463 | 230 | 8.36 | 97 | | | 60.8 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-450-4M-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 1.689 | 0.628 | 230 | 7.96 | 145 | | | 48.3 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-450-6T-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 1.121 | 0.230 | 205 | 5.29 | 67 | | | 48.9 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-450-6M-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 1.121 | 0.230 | 205 | 5.29 | 67 | | | 51.3 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-500-4T-F-400 IE3 | NRVU / UVU | Variabel hastighet | Ingen | | 2.722 | 0.585 | 215 | 9.63 | 83 | | | 60.6 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-500-6T-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 1.733 | 0.266 | 153 | 6.13 | 52 | | | 54.1 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-500-6M-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 1.733 | 0.266 | 153 | 6.13 | 52 | | | 47.6 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-630-6T-F-400 IE3 | NRVU / UVU | Variabel hastighet | Ingen | | 2.927 | 0.954 | 230 | 6.60 | 136 | | | 62.9 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-710-6T-F-400 IE3 | NRVU / UVU | Variabel hastighet | Ingen | | 2.360 | 2.461 | 230 | 4.23 | 496 | | | 59.4 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-800-6T-F-400 IE3 | NRVU / UVU | Variabel hastighet | Ingen | | 5.028 | 3.965 | 230 | 7.14 | 398 | | | 63.0 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |
| RFV-800-8T-F-400 | NRVU / UVU | Variabel hastighet | Ingen | | 4.178 | 1.723 | 230 | 5.94 | 187 | | | 58.0 | 2.1 | | Ikke aktuelt | Ikke aktuelt | | 2018 |