

**ECODESIGN INFORMATION**

Applies to non-residential ventilation units (NRVU)

According to Regulation EU No 1253/2014 of the European Commission, implementing Directive 2009/125/CE of European Parliament

SODECA, S.L.U.

www.sodeca.com

- b) Model
- c) Typology
- d) Drive type
- e) HRS type
- f) Thermal efficiency of heat recovery (%)
- g) Nominal flowrate
- h) Effective electric power input
- i) SFPint
- j) Face velocity at design flow rate
- k) Nominal external pressure
- l) Internal pressure drop of ventilation components
- m) Internal pressure drop of non-ventilation components
- n) Static efficiency of fans according to (EU) 327/2011
- o1) Max. internal leakage rate
- o2) Max. external leakage rate
- p) Energy performance of the filters
- q) Visual filter warning
- r) LWA radiated

| b)                      | c)         | d)                 | e)   | f) | g)    | h)    | i)     | j)   | k)  | l)  | m) | n)   | o1) | o2) | p)           | q)              | r)  | ERP  |
|-------------------------|------------|--------------------|------|----|-------|-------|--------|------|-----|-----|----|------|-----|-----|--------------|-----------------|-----|------|
|                         |            |                    |      | %  | m³/s  | kW    | W/m³/s | m/s  | Pa  | Pa  | Pa | %    | %   | %   |              |                 | dBA |      |
| UFX-12/12-0.5 G4+F6     | NRVU / UVU | Variabele snelheid | Geen |    | 0.704 | 0.426 | 230    | 2.09 | 138 | 84  |    | 35.7 | 2.4 |     | G4: G; F6: F | Zie instructies | 70  | 2018 |
| UFX-12/12-0.75 G4+F6    | NRVU / UVU | Variabele snelheid | Geen |    | 0.723 | 0.537 | 230    | 2.15 | 198 | 89  |    | 38.9 | 2.4 |     | G4: G; F6: F | Zie instructies | 73  | 2018 |
| UFX-12/12-1 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 0.742 | 0.653 | 230    | 2.20 | 264 | 94  |    | 40.2 | 2.4 |     | G4: G; F6: F | Zie instructies | 76  | 2018 |
| UFX-12/12-1.5 G4+F6 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 0.738 | 0.801 | 230    | 2.19 | 345 | 93  |    | 41.4 | 2.4 |     | G4: G; F6: F | Zie instructies | 78  | 2018 |
| UFX-12/12-2 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 0.713 | 1.165 | 230    | 2.12 | 527 | 86  |    | 42.2 | 2.4 |     | G4: G; F6: F | Zie instructies | 81  | 2018 |
| UFX-12/12-3 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 0.703 | 1.369 | 230    | 2.09 | 627 | 84  |    | 42.5 | 2.4 |     | G4: G; F6: F | Zie instructies | 85  | 2018 |
| UFX-15/15-0.75 G4+F6    | NRVU / UVU | Variabele snelheid | Geen |    | 1.456 | 0.697 | 230    | 2.22 | 84  | 77  |    | 37.8 | 2.4 |     | G4: G; F6: F | Zie instructies | 74  | 2018 |
| UFX-15/15-1 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.560 | 0.935 | 230    | 2.38 | 143 | 89  |    | 39.9 | 2.4 |     | G4: G; F6: F | Zie instructies | 77  | 2018 |
| UFX-15/15-1.5 G4+F6 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 1.594 | 1.071 | 230    | 2.43 | 178 | 93  |    | 41.0 | 2.4 |     | G4: G; F6: F | Zie instructies | 78  | 2018 |
| UFX-15/15-2 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.626 | 1.377 | 230    | 2.48 | 259 | 97  |    | 41.9 | 2.4 |     | G4: G; F6: F | Zie instructies | 79  | 2018 |
| UFX-15/15-3 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.640 | 1.716 | 230    | 2.50 | 348 | 98  |    | 42.2 | 2.4 |     | G4: G; F6: F | Zie instructies | 81  | 2018 |
| UFX-15/15-4 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.639 | 2.097 | 230    | 2.50 | 447 | 98  |    | 42.3 | 2.4 |     | G4: G; F6: F | Zie instructies | 83  | 2018 |
| UFX-18/18-1.5 G4+F6 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 1.399 | 0.975 | 230    | 2.13 | 174 | 85  |    | 49.0 | 2.4 |     | G4: G; F6: F | Zie instructies | 78  | 2018 |
| UFX-18/18-2 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.393 | 1.278 | 230    | 2.12 | 253 | 85  |    | 50.0 | 2.4 |     | G4: G; F6: F | Zie instructies | 83  | 2018 |
| UFX-18/18-3 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.386 | 1.574 | 230    | 2.11 | 330 | 84  |    | 50.3 | 2.4 |     | G4: G; F6: F | Zie instructies | 83  | 2018 |
| UFX-18/18-4 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.362 | 2.068 | 230    | 2.08 | 453 | 81  |    | 50.4 | 2.4 |     | G4: G; F6: F | Zie instructies | 85  | 2018 |
| UFX-18/18-5.5 G4+F6 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 1.333 | 2.639 | 230    | 2.03 | 590 | 78  |    | 51.4 | 2.4 |     | G4: G; F6: F | Zie instructies | 86  | 2018 |
| UFX-20/20-2 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 2.812 | 1.577 | 230    | 2.29 | 92  | 64  |    | 41.9 | 2.4 |     | G4: G; F6: F | Zie instructies | 75  | 2018 |
| UFX-20/20-3 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 2.918 | 2.024 | 230    | 2.37 | 138 | 69  |    | 42.2 | 2.4 |     | G4: G; F6: F | Zie instructies | 79  | 2018 |
| UFX-20/20-4 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 3.038 | 3.096 | 230    | 2.47 | 255 | 74  |    | 42.3 | 2.4 |     | G4: G; F6: F | Zie instructies | 81  | 2018 |
| UFX-20/20-5.5 G4+F6 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 3.076 | 3.687 | 230    | 2.50 | 321 | 76  |    | 43.0 | 2.4 |     | G4: G; F6: F | Zie instructies | 83  | 2018 |
| UFX-20/20-7.5 G4+F6 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 3.100 | 5.024 | 230    | 2.52 | 468 | 77  |    | 43.9 | 2.4 |     | G4: G; F6: F | Zie instructies | 85  | 2018 |
| UFX-20/20-10 G4+F6 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 3.087 | 6.229 | 230    | 2.51 | 597 | 77  |    | 44.3 | 2.4 |     | G4: G; F6: F | Zie instructies | 86  | 2018 |
| UFX-22/22-2 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 2.962 | 1.488 | 230    | 2.41 | 105 | 88  |    | 43.9 | 2.4 |     | G4: G; F6: F | Zie instructies | 75  | 2018 |
| UFX-22/22-3 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 3.037 | 1.893 | 230    | 2.47 | 159 | 93  |    | 44.1 | 2.4 |     | G4: G; F6: F | Zie instructies | 79  | 2018 |
| UFX-22/22-4 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 3.085 | 2.346 | 230    | 2.51 | 221 | 96  |    | 44.2 | 2.4 |     | G4: G; F6: F | Zie instructies | 81  | 2018 |
| UFX-22/22-5.5 G4+F6 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 3.121 | 3.402 | 230    | 2.54 | 367 | 98  |    | 45.0 | 2.4 |     | G4: G; F6: F | Zie instructies | 83  | 2018 |
| UFX-22/22-7.5 G4+F6 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 3.138 | 3.981 | 230    | 2.55 | 448 | 99  |    | 46.0 | 2.4 |     | G4: G; F6: F | Zie instructies | 84  | 2018 |
| UFX-22/22-10 G4+F6 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 3.138 | 5.300 | 230    | 2.55 | 630 | 99  |    | 46.3 | 2.4 |     | G4: G; F6: F | Zie instructies | 88  | 2018 |
| UFX-22/22-15 G4+F6 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 3.146 | 6.004 | 230    | 2.56 | 728 | 100 |    | 46.4 | 2.4 |     | G4: G; F6: F | Zie instructies | 89  | 2018 |
| UFX-25/25-3 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 4.358 | 2.080 | 230    | 2.21 | 84  | 78  |    | 42.1 | 2.4 |     | G4: G; F6: F | Zie instructies | 79  | 2018 |
| UFX-25/25-4 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 4.556 | 2.745 | 230    | 2.31 | 138 | 85  |    | 42.2 | 2.4 |     | G4: G; F6: F | Zie instructies | 81  | 2018 |
| UFX-25/25-5.5 G4+F6 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 4.702 | 3.516 | 230    | 2.39 | 204 | 91  |    | 42.9 | 2.4 |     | G4: G; F6: F | Zie instructies | 83  | 2018 |

**ECODESIGN INFORMATION**

Applies to non-residential ventilation units (NRVU)

According to Regulation EU No 1253/2014 of the European Commission, implementing Directive 2009/125/CE of European Parliament

SODECA, S.L.U.

www.sodeca.com

| b)                      | c)         | d)                 | e)   | f) | g)    | h)     | i)     | j)   | k)  | l)  | m) | n)   | o1) | o2) | p)           | q)                 | r)  | ERP  |
|-------------------------|------------|--------------------|------|----|-------|--------|--------|------|-----|-----|----|------|-----|-----|--------------|--------------------|-----|------|
|                         |            |                    |      | %  | m³/s  | kW     | W/m³/s | m/s  | Pa  | Pa  | Pa | %    | %   | %   |              | Zie<br>instructies | dBA |      |
| UFX-25/25-7.5 G4+F6 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 4.834 | 4.889  | 230    | 2.45 | 325 | 96  |    | 43.8 | 2.4 |     | G4: G; F6: F | Zie instructies    | 85  | 2018 |
| UFX-25/25-10 G4+F6 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 4.883 | 5.944  | 230    | 2.48 | 419 | 98  |    | 44.1 | 2.4 |     | G4: G; F6: F | Zie instructies    | 87  | 2018 |
| UFX-25/25-15 G4+F6 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 4.903 | 7.761  | 230    | 2.49 | 579 | 98  |    | 44.3 | 2.4 |     | G4: G; F6: F | Zie instructies    | 90  | 2018 |
| UFX-30/28-3 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 6.935 | 2.561  | 230    | 2.38 | 47  | 78  |    | 43.7 | 2.4 |     | G4: G; F6: F | Zie instructies    | 81  | 2018 |
| UFX-30/28-4 G4+F6 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 7.243 | 3.133  | 230    | 2.48 | 75  | 85  |    | 43.8 | 2.4 |     | G4: G; F6: F | Zie instructies    | 83  | 2018 |
| UFX-30/28-5.5 G4+F6 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 7.720 | 4.468  | 230    | 2.65 | 146 | 96  |    | 44.6 | 2.4 |     | G4: G; F6: F | Zie instructies    | 84  | 2018 |
| UFX-30/28-7.5 G4+F6 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 8.078 | 5.993  | 230    | 2.77 | 235 | 105 |    | 45.6 | 2.4 |     | G4: G; F6: F | Zie instructies    | 84  | 2018 |
| UFX-30/28-10 G4+F6 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 8.231 | 6.807  | 230    | 2.82 | 284 | 109 |    | 45.9 | 2.4 |     | G4: G; F6: F | Zie instructies    | 85  | 2018 |
| UFX-30/28-15 G4+F6 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 8.537 | 9.570  | 230    | 2.93 | 456 | 118 |    | 46.0 | 2.4 |     | G4: G; F6: F | Zie instructies    | 87  | 2018 |
| UFX-30/28-20 G4+F6 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 8.625 | 10.552 | 230    | 2.96 | 519 | 120 |    | 45.9 | 2.4 |     | G4: G; F6: F | Zie instructies    | 89  | 2018 |
| UFX-12/12-0.5 F6+F8     | NRVU / UVU | Variabele snelheid | Geen |    | 0.788 | 0.464  | 230    | 2.34 | 130 | 83  |    | 35.7 | 2.4 |     | F6: F; F8: A | Zie instructies    | 70  | 2018 |
| UFX-12/12-0.75 F6+F8    | NRVU / UVU | Variabele snelheid | Geen |    | 0.815 | 0.585  | 230    | 2.42 | 189 | 89  |    | 38.9 | 2.4 |     | F6: F; F8: A | Zie instructies    | 73  | 2018 |
| UFX-12/12-1 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 0.843 | 0.712  | 230    | 2.50 | 255 | 95  |    | 40.2 | 2.4 |     | F6: F; F8: A | Zie instructies    | 76  | 2018 |
| UFX-12/12-1.5 F6+F8 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 0.846 | 0.873  | 230    | 2.51 | 335 | 96  |    | 41.4 | 2.4 |     | F6: F; F8: A | Zie instructies    | 78  | 2018 |
| UFX-12/12-2 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 0.828 | 1.265  | 230    | 2.46 | 520 | 92  |    | 42.2 | 2.4 |     | F6: F; F8: A | Zie instructies    | 81  | 2018 |
| UFX-12/12-3 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 0.821 | 1.484  | 230    | 2.44 | 621 | 91  |    | 42.5 | 2.4 |     | F6: F; F8: A | Zie instructies    | 85  | 2018 |
| UFX-15/15-0.75 F6+F8    | NRVU / UVU | Variabele snelheid | Geen |    | 1.583 | 0.776  | 230    | 2.41 | 77  | 68  |    | 37.8 | 2.4 |     | F6: F; F8: A | Zie instructies    | 74  | 2018 |
| UFX-15/15-1 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.726 | 1.055  | 230    | 2.63 | 135 | 81  |    | 39.9 | 2.4 |     | F6: F; F8: A | Zie instructies    | 77  | 2018 |
| UFX-15/15-1.5 F6+F8 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 1.779 | 1.214  | 230    | 2.71 | 170 | 86  |    | 41.0 | 2.4 |     | F6: F; F8: A | Zie instructies    | 78  | 2018 |
| UFX-15/15-2 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.847 | 1.574  | 230    | 2.82 | 252 | 93  |    | 41.9 | 2.4 |     | F6: F; F8: A | Zie instructies    | 79  | 2018 |
| UFX-15/15-3 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.890 | 1.967  | 230    | 2.88 | 344 | 98  |    | 42.2 | 2.4 |     | F6: F; F8: A | Zie instructies    | 81  | 2018 |
| UFX-15/15-4 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.909 | 2.403  | 230    | 2.91 | 445 | 100 |    | 42.3 | 2.4 |     | F6: F; F8: A | Zie instructies    | 83  | 2018 |
| UFX-18/18-1.5 F6+F8 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 1.580 | 1.067  | 230    | 2.41 | 166 | 86  |    | 49.0 | 2.4 |     | F6: F; F8: A | Zie instructies    | 78  | 2018 |
| UFX-18/18-2 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.586 | 1.400  | 230    | 2.42 | 246 | 87  |    | 50.0 | 2.4 |     | F6: F; F8: A | Zie instructies    | 83  | 2018 |
| UFX-18/18-3 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.587 | 1.725  | 230    | 2.42 | 323 | 87  |    | 50.3 | 2.4 |     | F6: F; F8: A | Zie instructies    | 83  | 2018 |
| UFX-18/18-4 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.569 | 2.263  | 230    | 2.39 | 447 | 85  |    | 50.4 | 2.4 |     | F6: F; F8: A | Zie instructies    | 85  | 2018 |
| UFX-18/18-5.5 F6+F8 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 1.545 | 2.884  | 230    | 2.36 | 585 | 82  |    | 51.4 | 2.4 |     | F6: F; F8: A | Zie instructies    | 86  | 2018 |
| UFX-20/20-2 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 3.070 | 1.596  | 230    | 2.50 | 69  | 55  |    | 41.9 | 2.4 |     | F6: F; F8: A | Zie instructies    | 75  | 2018 |
| UFX-20/20-3 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 3.231 | 2.085  | 230    | 2.63 | 110 | 61  |    | 42.2 | 2.4 |     | F6: F; F8: A | Zie instructies    | 79  | 2018 |
| UFX-20/20-4 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 3.449 | 3.303  | 230    | 2.80 | 220 | 69  |    | 42.3 | 2.4 |     | F6: F; F8: A | Zie instructies    | 81  | 2018 |
| UFX-20/20-5.5 F6+F8 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 3.529 | 3.989  | 230    | 2.87 | 285 | 73  |    | 43.0 | 2.4 |     | F6: F; F8: A | Zie instructies    | 83  | 2018 |
| UFX-20/20-7.5 F6+F8 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 3.624 | 5.546  | 230    | 2.95 | 433 | 77  |    | 43.9 | 2.4 |     | F6: F; F8: A | Zie instructies    | 85  | 2018 |
| UFX-20/20-10 F6+F8 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 3.662 | 6.937  | 230    | 2.98 | 566 | 78  |    | 44.3 | 2.4 |     | F6: F; F8: A | Zie instructies    | 86  | 2018 |
| UFX-22/22-2 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 3.246 | 1.590  | 230    | 2.64 | 93  | 83  |    | 43.9 | 2.4 |     | F6: F; F8: A | Zie instructies    | 75  | 2018 |
| UFX-22/22-3 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 3.362 | 2.040  | 230    | 2.73 | 145 | 89  |    | 44.1 | 2.4 |     | F6: F; F8: A | Zie instructies    | 79  | 2018 |
| UFX-22/22-4 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 3.442 | 2.546  | 230    | 2.80 | 206 | 93  |    | 44.2 | 2.4 |     | F6: F; F8: A | Zie instructies    | 81  | 2018 |
| UFX-22/22-5.5 F6+F8 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 3.522 | 3.734  | 230    | 2.86 | 352 | 97  |    | 45.0 | 2.4 |     | F6: F; F8: A | Zie instructies    | 83  | 2018 |

**ECODESIGN INFORMATION**

Applies to non-residential ventilation units (NRVU)

According to Regulation EU No 1253/2014 of the European Commission, implementing Directive 2009/125/CE of European Parliament

SODECA, S.L.U.

www.sodeca.com

| b)                      | c)         | d)                 | e)   | f) | g)    | h)     | i)     | j)   | k)  | l)  | m) | n)   | o1) | o2) | p)           | q)              | r)  | ERP  |
|-------------------------|------------|--------------------|------|----|-------|--------|--------|------|-----|-----|----|------|-----|-----|--------------|-----------------|-----|------|
|                         |            |                    |      | %  | m³/s  | kW     | W/m³/s | m/s  | Pa  | Pa  | Pa | %    | %   | %   |              | Zie instructies | dBA |      |
| UFX-22/22-7.5 F6+F8 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 3.553 | 4.385  | 230    | 2.89 | 433 | 99  |    | 46.0 | 2.4 |     | F6: F; F8: A | Zie instructies | 84  | 2018 |
| UFX-22/22-10 F6+F8 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 3.570 | 5.870  | 230    | 2.90 | 615 | 100 |    | 46.3 | 2.4 |     | F6: F; F8: A | Zie instructies | 88  | 2018 |
| UFX-22/22-15 F6+F8 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 3.585 | 6.660  | 230    | 2.92 | 714 | 101 |    | 46.4 | 2.4 |     | F6: F; F8: A | Zie instructies | 89  | 2018 |
| UFX-25/25-3 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 4.722 | 2.251  | 230    | 2.40 | 74  | 69  |    | 42.1 | 2.4 |     | F6: F; F8: A | Zie instructies | 79  | 2018 |
| UFX-25/25-4 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 4.991 | 2.977  | 230    | 2.53 | 122 | 77  |    | 42.2 | 2.4 |     | F6: F; F8: A | Zie instructies | 81  | 2018 |
| UFX-25/25-5.5 F6+F8 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 5.207 | 3.818  | 230    | 2.64 | 183 | 84  |    | 42.9 | 2.4 |     | F6: F; F8: A | Zie instructies | 83  | 2018 |
| UFX-25/25-7.5 F6+F8 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 5.439 | 5.311  | 230    | 2.76 | 296 | 91  |    | 43.8 | 2.4 |     | F6: F; F8: A | Zie instructies | 85  | 2018 |
| UFX-25/25-10 F6+F8 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 5.548 | 6.455  | 230    | 2.81 | 385 | 95  |    | 44.1 | 2.4 |     | F6: F; F8: A | Zie instructies | 87  | 2018 |
| UFX-25/25-15 F6+F8 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 5.647 | 8.424  | 230    | 2.87 | 540 | 98  |    | 44.3 | 2.4 |     | F6: F; F8: A | Zie instructies | 90  | 2018 |
| UFX-30/28-3 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 7.401 | 2.670  | 230    | 2.54 | 37  | 64  |    | 43.7 | 2.4 |     | F6: F; F8: A | Zie instructies | 81  | 2018 |
| UFX-30/28-4 F6+F8 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 7.795 | 3.299  | 230    | 2.67 | 60  | 71  |    | 43.8 | 2.4 |     | F6: F; F8: A | Zie instructies | 83  | 2018 |
| UFX-30/28-5.5 F6+F8 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 8.446 | 4.803  | 230    | 2.89 | 124 | 84  |    | 44.6 | 2.4 |     | F6: F; F8: A | Zie instructies | 84  | 2018 |
| UFX-30/28-7.5 F6+F8 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 8.962 | 6.563  | 230    | 3.07 | 206 | 94  |    | 45.6 | 2.4 |     | F6: F; F8: A | Zie instructies | 84  | 2018 |
| UFX-30/28-10 F6+F8 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 9.186 | 7.512  | 230    | 3.15 | 254 | 99  |    | 45.9 | 2.4 |     | F6: F; F8: A | Zie instructies | 85  | 2018 |
| UFX-30/28-15 F6+F8 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 9.675 | 10.764 | 230    | 3.31 | 423 | 110 |    | 46.0 | 2.4 |     | F6: F; F8: A | Zie instructies | 87  | 2018 |
| UFX-30/28-20 F6+F8 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 9.815 | 11.920 | 230    | 3.36 | 485 | 113 |    | 45.9 | 2.4 |     | F6: F; F8: A | Zie instructies | 89  | 2018 |
| UFX-12/12-0.5 F7+F9     | NRVU / UVU | Variabele snelheid | Geen |    | 0.744 | 0.444  | 230    | 2.21 | 134 | 84  |    | 35.7 | 2.4 |     | F7: A; F9: A | Zie instructies | 70  | 2018 |
| UFX-12/12-0.75 F7+F9    | NRVU / UVU | Variabele snelheid | Geen |    | 0.767 | 0.559  | 230    | 2.28 | 194 | 89  |    | 38.9 | 2.4 |     | F7: A; F9: A | Zie instructies | 73  | 2018 |
| UFX-12/12-1 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 0.789 | 0.680  | 230    | 2.34 | 260 | 95  |    | 40.2 | 2.4 |     | F7: A; F9: A | Zie instructies | 76  | 2018 |
| UFX-12/12-1.5 F7+F9 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 0.789 | 0.835  | 230    | 2.34 | 340 | 94  |    | 41.4 | 2.4 |     | F7: A; F9: A | Zie instructies | 78  | 2018 |
| UFX-12/12-2 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 0.767 | 1.211  | 230    | 2.28 | 524 | 89  |    | 42.2 | 2.4 |     | F7: A; F9: A | Zie instructies | 81  | 2018 |
| UFX-12/12-3 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 0.758 | 1.422  | 230    | 2.25 | 624 | 87  |    | 42.5 | 2.4 |     | F7: A; F9: A | Zie instructies | 85  | 2018 |
| UFX-15/15-0.75 F7+F9    | NRVU / UVU | Variabele snelheid | Geen |    | 1.518 | 0.735  | 230    | 2.31 | 81  | 73  |    | 37.8 | 2.4 |     | F7: A; F9: A | Zie instructies | 74  | 2018 |
| UFX-15/15-1 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.640 | 0.991  | 230    | 2.50 | 139 | 86  |    | 39.9 | 2.4 |     | F7: A; F9: A | Zie instructies | 77  | 2018 |
| UFX-15/15-1.5 F7+F9 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 1.683 | 1.137  | 230    | 2.57 | 175 | 90  |    | 41.0 | 2.4 |     | F7: A; F9: A | Zie instructies | 78  | 2018 |
| UFX-15/15-2 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.731 | 1.468  | 230    | 2.64 | 256 | 95  |    | 41.9 | 2.4 |     | F7: A; F9: A | Zie instructies | 79  | 2018 |
| UFX-15/15-3 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.757 | 1.830  | 230    | 2.68 | 347 | 98  |    | 42.2 | 2.4 |     | F7: A; F9: A | Zie instructies | 81  | 2018 |
| UFX-15/15-4 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.764 | 2.234  | 230    | 2.69 | 447 | 99  |    | 42.3 | 2.4 |     | F7: A; F9: A | Zie instructies | 83  | 2018 |
| UFX-18/18-1.5 F7+F9 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 1.484 | 1.018  | 230    | 2.26 | 170 | 86  |    | 49.0 | 2.4 |     | F7: A; F9: A | Zie instructies | 78  | 2018 |
| UFX-18/18-2 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.484 | 1.335  | 230    | 2.26 | 250 | 86  |    | 50.0 | 2.4 |     | F7: A; F9: A | Zie instructies | 83  | 2018 |
| UFX-18/18-3 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.480 | 1.644  | 230    | 2.26 | 327 | 85  |    | 50.3 | 2.4 |     | F7: A; F9: A | Zie instructies | 83  | 2018 |
| UFX-18/18-4 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 1.458 | 2.158  | 230    | 2.22 | 451 | 83  |    | 50.4 | 2.4 |     | F7: A; F9: A | Zie instructies | 85  | 2018 |
| UFX-18/18-5.5 F7+F9 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 1.431 | 2.752  | 230    | 2.18 | 588 | 80  |    | 51.4 | 2.4 |     | F7: A; F9: A | Zie instructies | 86  | 2018 |
| UFX-20/20-2 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 2.938 | 1.592  | 230    | 2.39 | 81  | 60  |    | 41.9 | 2.4 |     | F7: A; F9: A | Zie instructies | 75  | 2018 |
| UFX-20/20-3 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 3.070 | 2.061  | 230    | 2.50 | 125 | 65  |    | 42.2 | 2.4 |     | F7: A; F9: A | Zie instructies | 79  | 2018 |
| UFX-20/20-4 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 3.233 | 3.204  | 230    | 2.63 | 240 | 72  |    | 42.3 | 2.4 |     | F7: A; F9: A | Zie instructies | 81  | 2018 |
| UFX-20/20-5.5 F7+F9 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 3.289 | 3.839  | 230    | 2.67 | 306 | 75  |    | 43.0 | 2.4 |     | F7: A; F9: A | Zie instructies | 83  | 2018 |

**ECODESIGN INFORMATION**

Applies to non-residential ventilation units (NRVU)

According to Regulation EU No 1253/2014 of the European Commission, implementing Directive 2009/125/CE of European Parliament

SODECA, S.L.U.

www.sodeca.com

| b)                      | c)         | d)                 | e)   | f) | g)                | h)     | i)                  | j)   | k)  | l)  | m) | n)   | o1) | o2) | p)           | q)              | r)  | ERP  |
|-------------------------|------------|--------------------|------|----|-------------------|--------|---------------------|------|-----|-----|----|------|-----|-----|--------------|-----------------|-----|------|
|                         |            |                    |      | %  | m <sup>3</sup> /s | kW     | W/m <sup>3</sup> /s | m/s  | Pa  | Pa  | Pa | %    | %   | %   |              | Zie instructies | dBA |      |
| UFX-20/20-7.5 F7+F9 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 3.344             | 5.274  | 230                 | 2.72 | 454 | 78  |    | 43.9 | 2.4 |     | F7: A; F9: A | Zie instructies | 85  | 2018 |
| UFX-20/20-10 F7+F9 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 3.354             | 6.558  | 230                 | 2.73 | 585 | 78  |    | 44.3 | 2.4 |     | F7: A; F9: A | Zie instructies | 86  | 2018 |
| UFX-22/22-2 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 3.099             | 1.538  | 230                 | 2.52 | 99  | 86  |    | 43.9 | 2.4 |     | F7: A; F9: A | Zie instructies | 75  | 2018 |
| UFX-22/22-3 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 3.192             | 1.964  | 230                 | 2.60 | 153 | 91  |    | 44.1 | 2.4 |     | F7: A; F9: A | Zie instructies | 79  | 2018 |
| UFX-22/22-4 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 3.254             | 2.442  | 230                 | 2.65 | 214 | 95  |    | 44.2 | 2.4 |     | F7: A; F9: A | Zie instructies | 81  | 2018 |
| UFX-22/22-5.5 F7+F9 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 3.309             | 3.559  | 230                 | 2.69 | 360 | 98  |    | 45.0 | 2.4 |     | F7: A; F9: A | Zie instructies | 83  | 2018 |
| UFX-22/22-7.5 F7+F9 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 3.331             | 4.171  | 230                 | 2.71 | 441 | 99  |    | 46.0 | 2.4 |     | F7: A; F9: A | Zie instructies | 84  | 2018 |
| UFX-22/22-10 F7+F9 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 3.338             | 5.567  | 230                 | 2.71 | 623 | 100 |    | 46.3 | 2.4 |     | F7: A; F9: A | Zie instructies | 88  | 2018 |
| UFX-22/22-15 F7+F9 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 3.349             | 6.310  | 230                 | 2.72 | 722 | 100 |    | 46.4 | 2.4 |     | F7: A; F9: A | Zie instructies | 89  | 2018 |
| UFX-25/25-3 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 4.533             | 2.160  | 230                 | 2.30 | 79  | 74  |    | 42.1 | 2.4 |     | F7: A; F9: A | Zie instructies | 79  | 2018 |
| UFX-25/25-4 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 4.765             | 2.853  | 230                 | 2.42 | 130 | 81  |    | 42.2 | 2.4 |     | F7: A; F9: A | Zie instructies | 81  | 2018 |
| UFX-25/25-5.5 F7+F9 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 4.943             | 3.655  | 230                 | 2.51 | 194 | 88  |    | 42.9 | 2.4 |     | F7: A; F9: A | Zie instructies | 83  | 2018 |
| UFX-25/25-7.5 F7+F9 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 5.121             | 5.083  | 230                 | 2.60 | 312 | 94  |    | 43.8 | 2.4 |     | F7: A; F9: A | Zie instructies | 85  | 2018 |
| UFX-25/25-10 F7+F9 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 5.197             | 6.179  | 230                 | 2.64 | 404 | 97  |    | 44.1 | 2.4 |     | F7: A; F9: A | Zie instructies | 87  | 2018 |
| UFX-25/25-15 F7+F9 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 5.252             | 8.065  | 230                 | 2.66 | 561 | 99  |    | 44.3 | 2.4 |     | F7: A; F9: A | Zie instructies | 90  | 2018 |
| UFX-30/28-3 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 7.165             | 2.618  | 230                 | 2.45 | 42  | 72  |    | 43.7 | 2.4 |     | F7: A; F9: A | Zie instructies | 81  | 2018 |
| UFX-30/28-4 F7+F9 IE3   | NRVU / UVU | Variabele snelheid | Geen |    | 7.513             | 3.219  | 230                 | 2.57 | 68  | 79  |    | 43.8 | 2.4 |     | F7: A; F9: A | Zie instructies | 83  | 2018 |
| UFX-30/28-5.5 F7+F9 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 8.070             | 4.636  | 230                 | 2.76 | 136 | 91  |    | 44.6 | 2.4 |     | F7: A; F9: A | Zie instructies | 84  | 2018 |
| UFX-30/28-7.5 F7+F9 IE3 | NRVU / UVU | Variabele snelheid | Geen |    | 8.498             | 6.271  | 230                 | 2.91 | 222 | 101 |    | 45.6 | 2.4 |     | F7: A; F9: A | Zie instructies | 84  | 2018 |
| UFX-30/28-10 F7+F9 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 8.682             | 7.148  | 230                 | 2.97 | 271 | 105 |    | 45.9 | 2.4 |     | F7: A; F9: A | Zie instructies | 85  | 2018 |
| UFX-30/28-15 F7+F9 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 9.068             | 10.131 | 230                 | 3.11 | 442 | 115 |    | 46.0 | 2.4 |     | F7: A; F9: A | Zie instructies | 87  | 2018 |
| UFX-30/28-20 F7+F9 IE3  | NRVU / UVU | Variabele snelheid | Geen |    | 9.179             | 11.190 | 230                 | 3.14 | 505 | 117 |    | 45.9 | 2.4 |     | F7: A; F9: A | Zie instructies | 89  | 2018 |